

IB962

**14th Generation Intel®
Core™ Ultra Processor
(MTL-U/H Platform)
3.5" Disk-Size SBC**

User's Manual

Version 1.0
(July 2024)

Copyright

© 2024 IBASE Technology, Inc. All rights reserved.

No part of this publication may be reproduced, copied, stored in a retrieval system, translated into any language or transmitted in any form or by any means, electronic, mechanical, photocopying, or otherwise, without the prior written consent of IBASE Technology, Inc. (hereinafter referred to as "IBASE").

Disclaimer

IBASE reserves the right to make changes and improvements to the products described in this document without prior notice. Every effort has been made to ensure the information in the document is correct; however, IBASE does not guarantee this document is error-free.

IBASE assumes no liability for incidental or consequential damages arising from misapplication or inability to use the product or the information contained herein, nor for any infringements of rights of third parties, which may result from its use.

Trademarks

All the trademarks, registrations and brands mentioned herein are used for identification purposes only and may be trademarks and/or registered trademarks of their respective owners.

Compliance



This product has passed CE Class B tests for environmental specifications and limits. This product is in accordance with the directives of the European Union (EU). In a domestic environment, this product may cause radio interference in which case users may be required to take adequate measures.



This product has been tested and found to comply with the limits for a Class B device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with manufacturer's instructions, may cause harmful interference to radio communications.

WEEE



This product must not be disposed of as normal household waste, in accordance with the EU directive of for waste electrical and electronic equipment (WEEE - 2012/19/EU). Instead, it should be disposed of by returning it to a municipal recycling collection point. Check local regulations for disposal of electronic products.

Green IBASE



This product complies with RoHS 2 restrictions, which prohibit the use of certain hazardous substances in electrical and electronic equipment. The following substances must not exceed the specified concentrations:

- Hexavalent chromium: 1,000 ppm
- Poly-brominated biphenyls (PBBs): 1,000 ppm
- Poly-brominated diphenyl ethers (PBDEs): 1,000 ppm
- Cadmium: 100 ppm
- Mercury: 1,000 ppm
- Lead: 1,000 ppm
- Bis(2-ethylhexyl) phthalate (DEHP): 1,000 ppm
- Butyl benzyl phthalate (BBP): 1,000 ppm
- Dibutyl phthalate (DBP): 1,000 ppm
- Diisobutyl phthalate (DIBP): 1,000 ppm

Important Safety Information

Environmental conditions:

- Use this product in environments with ambient temperatures between 0°C and 60°C.
- Do not leave this product in an environment where the storage temperature may be below -20° C or above 80° C. To prevent from damages, the product must be used in a controlled environment.

Care for your iBASE products:

- Before cleaning the PCB, unplug all cables and remove the battery.
- Clean the PCB with a circuit board cleaner or degreaser, or use cotton swabs and alcohol.



WARNING

Attention during use:

- Do not use this product near water.
- Do not spill water or any other liquids on this product.
- Do not place heavy objects on the top of this product.

Anti-static precautions

- Wear an anti-static wrist strap to avoid electrostatic discharge.
- Place the PCB on an anti-static kit or mat.
- Hold the edges of PCB when handling.
- Touch the edges of non-metallic components of the product instead of the surface of the PCB.
- Ground yourself by touching a grounded conductor or a grounded bit of metal frequently to discharge any static.



CAUTION

There is danger of explosion if the internal lithium-ion battery is replaced by an incorrect type. Replace only with the same or equivalent type recommended by the manufacturer. Dispose of used batteries according to the manufacturer's instructions or recycle them at a local recycling facility or battery collection point.

Warranty Policy

- **IBASE standard products:**

24-month (2-year) warranty from the date of shipment. If the date of shipment cannot be ascertained, the product serial numbers can be used to determine the approximate shipping date.

- **3rd-party parts:**

12-month (1-year) warranty from delivery for the 3rd-party parts that are not manufactured by IBASE, such as CPU, CPU cooler, memory, storage devices, power adapter, panel and touchscreen.

- * PRODUCTS THAT FAIL DUE TO MISUSE, ACCIDENT, IMPROPER INSTALLATION OR UNAUTHORIZED REPAIR SHALL BE TREATED AS OUT OF WARRANTY AND CUSTOMERS SHALL BE BILLED FOR REPAIR AND SHIPPING CHARGES.

Technical Support & Services

1. Visit the IBASE website at www.ibase.com.tw to find the latest information about the product.
2. If repair service is required, please log in to the RMA system of the website or contact your distributor or sales representative for assistance.

Table of Contents

Chapter 1	General Information.....	1
1.1	Introduction	2
1.2	Features	2
1.3	Packing List.....	3
1.4	Optional Accessories	3
1.5	Specifications	4
1.6	Block Diagram	6
1.7	Board Pictures	7
1.8	Dimensions	10
Chapter 2	Hardware Configuration	11
2.1	Essential Installations	12
2.2	Setting the Jumpers.....	13
2.3	Jumper & Connector Locations.....	14
2.4	Jumpers Quick Reference	15
2.4.1	J1: Clear RTC	15
2.4.2	JP1: LVDS Brightness Power Selection.....	16
2.4.3	JP2: eDP Power Selection	16
2.4.4	JP3: LVDS Power Selection	17
2.4.5	JP4: Sierra EM919x 5G card USB/PCIe Select	17
2.4.6	JP5: AT/ATX Select.....	18
2.4.7	J5: Flash Descriptor Security Override (Factory use only)	18
2.4.8	J6: Clear CMOS	18
2.5	Connectors Quick Reference.....	19
2.5.1	CN1: eDP Connector.....	21
2.5.2	CN2, CN3: SATA #0 / SATA #1	22
2.5.3	CN4: 2.5G LAN i226LM/i226V	23
2.5.4	CN5: USB3 #2 / USB2 #2.....	23
2.5.5	CN6: DP++ / HDMI.....	24
2.5.6	CN7: USB3 TCP#2 #3.....	24
2.5.7	CN8: COM1 Port	25
2.5.8	CN9: SIM Socket.....	26
2.5.9	J2: LVDS Backlight Connector	26
2.5.10	J3: Audio Connector.....	27
2.5.11	J4: COM2 Port	28
2.5.12	J7: DDR5 SO-DIMM CHA	29

2.5.13	J8: Battery Connector	29
2.5.14	J9, J13: LVDS CH-B / CH-A.....	30
2.5.15	J10: Digital I/O (4in, 4out)	31
2.5.16	J11: eSPI Debug (Factory Use Only)	31
2.5.17	J12: DDR5 SO-DIMM CHB	31
2.5.18	J14: M.2 B-Key 3052	32
2.5.19	J15: SPI Flash Connector (Factory use only)	32
2.5.20	J16: USB2 #5/#6.....	32
2.5.21	J17: DC-IN (12-24V)	33
2.5.22	J18: M.2 M-Key 2280.....	33
2.5.23	J19: SATA Power Connector	34
2.5.24	J20: Front Panel Connector	35
2.5.25	J21: PWM programming (Factory use only)	36
2.5.26	J22: M.2 E-Key 2230 W/CNVI.....	36
2.5.27	CPU_FAN1: CPU Fan Power Connector	37
Chapter 3	Drivers Installation	39
3.1	Introduction	40
3.2	Intel® Chipset Software Installation Utility	40
3.3	VGA Driver Installation.....	42
3.4	Intel(R) Smartsound Drivers Installation	44
3.5	HD Audio Driver Installation	45
3.6	LAN Driver Installation	46
3.7	Intel® ME Drivers Installation	47
3.8	Intel® Serial IO Drivers Installation.....	48
3.9	Intel® PMT Drivers Installation.....	49
3.10	Intel® NPU IO Drivers Installation	50
Chapter 4	BIOS Setup.....	51
Appendix	73
A.	I/O Port Address Map	74
B.	Interrupt Request Lines (IRQ)	75
C.	Watchdog Timer Configuration.....	76
D.	Onboard Connector Reference Types.....	80
E.	USB Power Control Bit.....	80

This page is intentionally left blank.

Chapter 1

General Information

The information provided in this chapter includes:

- Features
- Packing List
- Optional Accessories
- Specifications
- Block Diagram
- Board Pictures
- Board Dimensions

1.1 Introduction

Powered by the latest 14th Gen Intel® Core™ Ultra 7/5 100 Series mobile processors, the IB962 ensures high performance and exceptional efficiency for a wide range of applications. Accompanied by 2x DDR5 SO-DIMM sockets with a maximum capacity of 64GB, the motherboard guarantees seamless multitasking and improved system responsiveness. Graphics support is provided by HDMI, DP++, LVDS, and eDP for independent display outputs. Two Intel® I226LM and I226V 2.5G LAN ports ensure high-speed networking for seamless data transfer. Equipped with 3x USB 2.0, 3x USB 3.2, 2x COM, and 2x SATA III ports, the IB962 offers exceptional peripheral connectivity, and 3x M.2 slots (M-Key + E-Key + B-Key) enhance expandability options. Additionally, the motherboard supports 5G, digital I/O (4-in/4-out), dTPM/fTPM, and a watchdog timer for robust system security and reliability.



1.2 Features

- Onboard 14th Gen Intel® Core™ Ultra 7/5 100 Series mobile processors
- 2x DDR5 SO-DIMM, Max. 64GB
- Supports HDMI, DP++, LVDS and eDP
- 1x Intel® I226LM 2.5G LAN, 1x Intel® I226V 2.5G LAN
- 3x USB 2.0, 3x USB 3.2, 2x COM, 2x SATA III
- 3x M.2 slots (M-Key + E-Key + B-Key)
- Supports 5G, digital I/O (4-in/4-out), dTPM/fTPM & watchdog timer

1.3 Packing List

Your IB962 package should include the items listed below. If any of the items below is missing, contact the distributor or dealer from whom you purchased the product.

- IB962 SBC

1.4 Optional Accessories

IBASE provides the following optional accessories:

- Cable Kit (IB76A-2)
Including:
DC-In power cable (PW592) x1
COM ports cable (PK1H) x1
SATA & HDD power cable (SATA-53A) x1
USB 2.0 cable (USB29) x1
- Audio cable (Audio-18)
- Heat spreader (HSIB962-1)
- Heat sink (HSIB962-A)

1.5 Specifications

Models	
Product Name	IB962AF-165H (Ultra 165H CPU onboard) IB962AF-165U (Ultra 165U CPU onboard) IB962AF-135H (Ultra 135H CPU onboard) IB962AF-135U (Ultra 135U CPU onboard)
CPU Type	Intel® Core™ Ultra 100 series (U/H series), 4nm BGA-2049 package (50mm x 25mm x 1.35mm),
CPU Type	Intel Core™ Ultra 7 – 165H (28W TDP) [C018UTL7G14010100P] Intel Core™ Ultra 7 – 165U (15W TDP) [C018UTL7G17010100P] Intel Core™ Ultra 5 – 135H (28W TDP) [C018UTL5G17010100P] Intel Core™ Ultra 5 – 135U (15W TDP) [C018UTL5G16010100P]
Specifications	
Form Factor	3.5" disk-size SBC
Memory	Intel® Core™ Ultra 100 series integrated memory controller, DDR5-5600, SO-DIMM x 2, Max.= 64GB
BIOS	AMI
Graphics	Intel 14th Gen. Core series built-in Iris Xe Graphics
Display Output	Support 4 x displays - eDP ** Resolution up to 7680 x 4320 @ 30Hz** - LVDS ** Resolution up to 1920 x 1200 @ 60 Hz** - DisplayPort 1.4a x 1 (DP++)@ edge connector ** Resolution up to 7680 x 4320 @ 30Hz** - HDMI 2.0 x 1 @ edge connector ** Resolution up to 3840 x 2160 @ 60Hz **
LAN	Intel® I226LM as 1st LAN, I226V as 2nd LAN
Super I/O	Fintek F81804U-I
Storage Interface	M.2 (M2280 for NVMe)
Mini Type Slots	1x M.2 (M-Key, Type:2280, supports NVMe with PCI-E(4x) signal only) 1x M.2 (E-Key, Type:2230, supports CNVi) 1x M.2 (B-Key, Type:3052, supports 5G/LTE)
Audio	14th Gen Intel® Core™ Ultra Series processor built-in HD audio + ALC888S codec
Watchdog Timer	Yes (256 segments, 0, 1, 2...255 sec / min)
H/W Monitor	Yes


Power Requirement	+12V (-10% tolerance) ~ +24V (+10% tolerance) DC-in
TPM	dTPM/fTPM
Dimensions	102.22 x 147.01 mm (4.02" x 5.8")
RoHS 2	Yes
Certification	CE, FCC Class B

I/O Ports	
Display	<ul style="list-style-type: none"> • DisplayPort • eDP & LVDS • HDMI
LAN	2 x RJ45 for 2.5 Gigabit Ethernet
USB	<ul style="list-style-type: none"> • 3x USB 2.0 (1x Type-A, 2x via pin header) • 3x USB 3.2 (Type-A)
Serial	<ul style="list-style-type: none"> • 2x RS232/422/485
SATA	2 x SATA III
Digital IO	4-In & 4-Out
Expansion Slots	<ul style="list-style-type: none"> • 1x M.2 (M-Key, Type:2280, supports NVMe with PCIe(4x) signal only) • 1x M.2 (E-Key, Type:2230, supports CNVi) • 1x M.2 (B-Key, Type:3052, supports 5G/LTE)
Operating System	Windows 10 Linux Ubuntu / Fedora

Environmental	
Temperature	<ul style="list-style-type: none"> • Operation: 0 ~ 60 °C (32 ~ 140 °F) • Storage: -20 ~ 80 °C (-4 ~ 176 °F)
Relative Humidity	0 ~ 90 %, non-condensing at 60 °C


All specifications are subject to change without prior notice.

1.6 Block Diagram




1.7 Board Pictures

Top View




Bottom View




M.2 @2230
(E-Key)

SIM slot

CPU




I/O View



Function	Connector
Dual 2.5 GbE Ports	CN4
USB Ports	CN5, CN7
DP++ / HDMI	CN6
COM1 Serial Port	CN8

1.8 Dimensions



Chapter 2

Hardware Configuration


This section provides information on jumper settings and connectors on the IB962 in order to set up a workable system. On top of that, you will also need to install crucial pieces such as the CPU and the memory before using the product. The topics covered are:

- Essential installations
- Jumpers and connectors

2.1 Essential Installations

2.1.1 Installing the Memory

The IB962 supports TWO memory socket for DDR5 modules. To install a module, locate the memory slot on the board and perform the following steps:




1. Align the key of the memory module with that on the memory slot and insert the module slantwise.
2. Gently push the module in an upright position until the clips of the slot close to hold the module in place when the module touches the bottom of the slot.

To remove the module, press the clips outwards with both hands, and the module will pop-up.


2.2 Setting the Jumpers

Set up and configure your IB962 by using jumpers for various settings and features according to your needs and applications. Contact your supplier if you have doubts about the best configuration for your use.

Jumpers are short-length conductors consisting of several metal pins with a non-conductive base mounted on the circuit board. Jumper caps are used to have the functions and features enabled or disabled. If a jumper has 3 pins, you can connect either PIN1 to PIN2 or PIN2 to PIN3 by shorting.



A 3-pin jumper




A jumper cap

Refer to the illustration below to set jumpers.

Pin closed	Jumper	Setting
Open		
1-2		
2-3		

When two pins of a jumper are encased in a jumper cap, this jumper is **closed**, i.e. turned **On**.
When a jumper cap is removed from two jumper pins, this jumper is **open**, i.e. turned **Off**.


2.3 Jumper & Connector Locations





2.4 Jumpers Quick Reference


Jumper	Function
J1	Clear RTC
JP1	LVDS Brightness Power Selection
JP2	eDP Power Selection
JP3	LVDS Power Selection
JP4	Sierra EM919x 5G card USB/PCIe Select
JP5	AT/ATX Selection
J5	Flash Descriptor Security Override
J6	Clear CMOS Data

2.4.1 J1: Clear RTC




Function	Pin closed	Setting
Normal	1-2	1 
Clear RTC	2-3	1 

2.4.2 JP1: LVDS Brightness Power Selection




Function	Pin closed	Setting
3.3V (default)	1-2	1
5V	2-3	1

2.4.3 JP2: eDP Power Selection




Function	Pin closed	Setting
3.3V (default)	1-2	1
5V	2-3	1

2.4.4 JP3: LVDS Power Selection




Function	Pin closed	Setting
3.3V (default)	1-2	1
5V	2-3	1

2.4.5 JP4: Sierra EM919x 5G card USB/PCIe Select



Function	Pin closed	Setting
USB (default)	1-2	1
PCIe	2-3	1


2.4.6 JP5: AT/ATX Select



Function	Pin closed	Setting
ATX	Open (default)	
AT	Close	

2.4.7 J5: Flash Descriptor Security Override (Factory use only)



2.4.8 J6: Clear CMOS




Function	Pin closed	Setting
Normal	1-2	1
Clear CMOS	2-3	1

2.5 Connectors Quick Reference

Connectors	Function
CN1	eDP Connector
CN2, CN3	SATA #0 / #1 Ports
CN4	2.5G LAN i226LM/i226V Ports
CN5	USB3 #2 / USB2 #2 Ports
CN6	DP++ /HDMI
CN7	USB3 TCP#2 #3
CN8	COM1 Port
CN9	SIM Socket
J1	Clear RTC
J2	LVDS Backligh Connector
J3	Audio Connector
J4	COM2 Port
J7	DDR5 SO-DIMM CHA
J8	Battery Connector
J9	LVDS CH-B
J10	Digital I/O (4in, 4out)
J11	eSPI DEBUG (Factory use only)
J12	DDR SO-DIMM CHB
J13	LVDS CH-A
J14	M.2 B-Key 3052
J15	SPI Flash Connector (Factory use only)
J16	USB2 #5/#6
J17	DC-IN (12-24V)
J18	M.2 M-key 2280
J19	SATA Power Connector
J20	Front Panel Connector
J21	PWM Programming (Factory use only)
J22	M.2 E-Key 2230 W/CNVI
CPU_FAN1	CPU Fan Power Connector




2.5.1 CN1: eDP Connector



Pin	Assignment	Pin	Assignment
1	eDP Vcc	21	TXN0
2	eDP Vcc	22	TXP1
3	eDP Vcc	23	Ground
4	eDP Vcc	24	AUXP
5	eDP Vcc	25	AUXN
6	Ground	26	NC
7	Ground	27	+3.3V
8	Ground	28	EDP BKLT (+12V)
9	Ground	29	NC
10	Hot Plug detect	30	Ground
11	Ground	31	+5V
12	TXN3	32	NC
13	TXP3	33	Back Light Control
14	Ground	34	Back Light Enable
15	TXN2	35	EDP BKLT (+12V)
16	TXP2	36	+3.3V
17	Ground	37	Ground
18	TXN1	38	NC
19	TXP1	39	NC
20	Ground	40	NC


* KEL_SSL00-40S

2.5.2 CN2, CN3: SATA #0 / SATA #1




Pin	Assignment
1	Ground
2	TX+
3	TX-
4	Ground
5	RX-
6	RX+
7	Ground


2.5.3 CN4: 2.5G LAN i226LM/i226V




2.5.4 CN5: USB3 #2 / USB2 #2




2.5.5 CN6: DP++ / HDMI



2.5.6 CN7: USB3 TCP#2 #3




2.5.7 CN8: COM1 Port




Pin	Assignment		
	RS-232	RS-422	RS-485
1	DCD	TX-	DATA-
2	RX	TX+	DATA+
3	TX	RX+	NC
4	DTR	RX-	NC
5	Ground	Ground	Ground
6	DSR	NC	NC
7	RTS	NC	NC
8	CTS	NC	NC
9	RI	NC	NC
10	NC	NC	NC

2.5.8 CN9: SIM Socket




2.5.9 J2: LVDS Backlight Connector



* E-Call_0110-161-040

Pin	Assignment
1	+12V
2	Backlight Enable
3	Brightness Control
4	GND


2.5.10 J3: Audio Connector



* HK_DF11-12S-PA66H


Pin	Assignment	Pin	Assignment
1	LINE OUT_L	2	LINE OUT_R
3	FRONT_JD	4	GND
5	LINE IN_L	6	LINE IN_R
7	LINE _JD	8	GND
9	MIC_L	10	MIC_R
11	MIC_JD	12	GND

2.5.11 J4: COM2 Port




Pin	Assignment		
	RS-232	RS-422	RS-485
1	DCD	TX-	DATA-
2	RX	TX+	DATA+
3	TX	RX+	NC
4	DTR	RX-	NC
5	Ground	Ground	Ground
6	DSR	NC	NC
7	RTS	NC	NC
8	CTS	NC	NC
9	RI	NC	NC
10	NC	NC	NC


2.5.12 J7: DDR5 SO-DIMM CHA



2.5.13 J8: Battery Connector




2.5.14 J9, J13: LVDS CH-B / CH-A



Hirose_DF20G-20DP-1V(56)

Pin	Assignment	Pin	Assignment
1	TX0P	2	TX0N
3	GND	4	GND
5	TX1P	6	TX1N
7	GND	8	GND
9	TX2P	10	TX2N
11	GND	12	GND
13	CLKP	14	CLKN
15	GND	16	GND
17	TX3P	18	TX3N
19	+3.3V	20	+3.3V

2.5.15 J10: Digital I/O (4in, 4out)




* E-Call_0196-01-200-100


Pin	Assignment	Pin	Assignment
1	Ground	2	+5V
3	Out3	4	Out1
5	Out2	6	Out0
7	IN3	8	IN1
9	IN2	10	IN0

2.5.16 J11: eSPI Debug (Factory Use Only)

2.5.17 J12: DDR5 SO-DIMM CHB




2.5.18 J14: M.2 B-Key 3052



2.5.19 J15: SPI Flash Connector (Factory use only)


2.5.20 J16: USB2 #5/#6



* HK_DF11-8S-PA66H

Pin	Assignment	Pin	Assignment
1	+5V	2	GND
3	USB_PN	4	USB_PP
5	USB_PP	6	USB_PN
7	GND	8	+5V


2.5.21 J17: DC-IN (12-24V)




* HK_WAFER396-2S-WV

Pin	Assignment
1	DC_IN
2	GND

2.5.22 J18: M.2 M-Key 2280




2.5.23 J19: SATA Power Connector



* E-Call_0110-071-040

Pin	Assignment
1	+5V
2	GND
3	GND
4	NC

2.5.24 J20: Front Panel Connector




* E-Call_0126-01-203-080

Pin	Assignment	Pin	Assignment
1	Power BTN	2	Power BTN
3	HDD LED+	4	HDD LED-
5	Reset BTN	6	Reset BTN
7	Power LED+	8	Power LED-


This connector provides interfaces for the following functions.

- ATX Power ON Switch (Pins 1 and 2)**
 The 2 pins make an “ATX Power Supply On/Off Switch” for the system that connects to the power switch on the case. When pressed, the power switch will force the system to power on. When pressed again, it will power off the system.
- Hard Disk Drive LED Connector (Pins 3 and 4)**
 This connector connects to the hard drive activity LED on control panel. This LED will flash when the HDD is being accessed.
- Reset Switch (Pins 5 and 6)**
 The reset switch allows you to reset the system without turning the main power switch off and then on again. Orientation is not required when making a connection to this header.
- Power LED: Pins 7 and 8**
 This connector connects to the system power LED on control panel. This LED will light when the system turns on.


2.5.25 J21: PWM programming (Factory use only)



2.5.26 J22: M.2 E-Key 2230 W/CNVI



2.5.27 CPU_FAN1: CPU Fan Power Connector



* PWM Only

Pin	Assignment
1	Ground
2	+12V
3	Rotation detection
4	Control

This page is intentionally left blank.

Chapter 3

Drivers Installation

This chapter introduces installation of the following drivers:

- Intel® Chipset Software Installation Utility
- HDD Graphics Drivers
- Smartsound Drivers
- HD Audio Drivers
- LAN Drivers
- Intel® ME Drivers
- Intel® Serial I/O Drivers
- Intel® PMT Drivers
- Intel® NPU IO Drivers

3.1 Introduction

This section describes the installation procedures for software and drivers. The contents of this section include the following:

Note: After installing your Windows operating system, you must install the Intel® Chipset Software Installation Utility first before proceeding with the drivers installation.

3.2 Intel® Chipset Software Installation Utility

The Intel® Chipset drivers should be installed first before the software drivers to install INF files for Plug & Play function for Intel chipset components. Follow the instructions below to complete the installation.


1. Go to the product's download page. Download the compressed drivers file to your computer. Double-click the file to decompress it. After decompression, double-click 'CDGuide' to access the main drivers page, as shown below. Click **Intel** on the left pane and then **Intel(R) Meteor Lake-P/PS/U Chipset Drivers** on the right pane.



- Click **Intel(R) Chipset Software Installation Utility**.



- When the *Welcome* screen to the Intel® Chipset Device Software appears, click **Next** to continue.
- Accept the terms in the software license agreement.
- On the *Readme File Information* screen, click **Install**.




- After completing the installation, click **Finish** to complete the setup process.

3.3 VGA Driver Installation

1. Click **Intel** on the left pane and then **Intel(R) Meteor Lake-P/PS/U Chipset Drivers** on the right pane.




2. Click **Intel(R) HD Graphics Driver**.




3. Click **Begin installation**.



- Click **I agree** in the INTEL SOFTWARE LICENSE AGREEMENT screen.



- Click **Start** for the installer to install the following components:
 - Intel Graphics Driver
 - Intel Graphics Command Center
- When installation has been completed, click **Finish**.



3.4 Intel(R) Smartsound Drivers Installation

1. Click **Intel** on the left pane and then **Intel(R) Meteor Lake-P/PS/U Chipset Drivers** on the right pane. Click **Intel(R) Smartsound Drivers** on the right page.



2. Run the file in the path shown below for the InstallShield Wizard to start and complete the installation of the Intel Smartsound drivers. When installation has been completed, press any key to continue.



3.5 HD Audio Driver Installation


1. Click **Intel** on the left pane and then **Intel(R) Meteor Lake-P/PS/U Chipset Drivers** on the right pane. Click **Realtek Audio Drivers**.



2. Click **Realtek Audio DCH Drivers**.



3. Click **Next** when the Welcome to the InstallShield Wizard for Realtek Audio Driver screen appears. After the Installshield Wizard has completed the installation, restart the computer.



3.6 LAN Driver Installation


1. Click **Intel** on the left pane and then **Intel(R) Meteor Lake-P/PS/U Chipset Drivers** on the right pane.



2. Click **Intel(R) PRO LAN Network Drivers**..



3. On the *Intel® Network Connections* screen, click **Install Drivers and Software**.
4. When the Welcome to the install wizard for Intel(R) Network Connections screen appears, click **Next**.
5. Accept the terms in the software license agreement and click **Next**.
6. On the *Setup Options* screen, click the checkbox to select the desired driver(s) for installation. Then click **Next** to continue.



7. On the *Ready to Install the Program* screen, click **Install** to begin the installation. When the Install wizard has completed the installation, click **Finish**.

3.7 Intel® ME Drivers Installation

1. Click **Intel** on the left pane and then **Intel(R) Meteor Lake-P/PS/U Chipset Drivers** on the right pane.



2. Click **Intel(R) ME Drivers**.



3. When the Welcome screen appears, click **Next**.
4. Accept the terms in the license agreement and click **Next**.
5. In the Destination Folder screen, click **Next** to install to the default folder, or click Change to choose another destination folder.
6. After Intel Management Engine Components have been successfully installed, click **Finish**.

You have successfully installed the following components:

- Intel® Management Engine Interface
- Serial Over LAN
- Intel® Wireless Manageability Driver
- Local Management Service
- Intel® Trusted Connect Service

3.8 Intel® Serial IO Drivers Installation

1. Click **Intel** on the left pane and then **Intel(R) Meteor Lake-P/PS/U Chipset Drivers** on the right pane.



2. Click **Intel(R) Serial IO Drivers**.



3. When the Welcome screen appears, click **Next**.
4. Accept the terms in the license agreement and click **Next**.
5. In both the Readme File Information and Confirmation screens, click **Next**. When you successfully finished the installation, click **Finish**.



3.9 Intel® PMT Drivers Installation

1. Click **Intel** on the left pane and then **Intel(R) Meteor Lake-P/PS/U Chipset Drivers** on the right pane.



2. Click **Intel(R) PMT Drivers**.



3. Run the file in the path shown below for the InstallShield Wizard to start and complete the installation of the Intel PMT drivers. When installation has been completed, press any key to continue.



3.10 Intel® NPU IO Drivers Installation

1. Click **Intel** on the left pane and then **Intel(R) Meteor Lake-P/PS/U Chipset Drivers** on the right pane.



2. Click **Intel(R) NPU IO Drivers**.



3. Run the file in the path shown below for the InstallShield Wizard to start and complete the installation of the drivers. When installation has been completed, press any key to continue.



Chapter 4

BIOS Setup

This chapter describes the different settings available in the AMI BIOS that comes with the board. The topics covered in this chapter are as follows:

- Main Settings
- Advanced Settings
- Chipset Settings
- Security Settings
- Boot Settings
- Save & Exit
- MEBx

4.1 Introduction

The BIOS (Basic Input/Output System) installed in the ROM of your computer system supports Intel® processors. The BIOS provides critical low-level support for standard devices such as disk drives, serial ports and parallel ports. It also provides password protection as well as special support for detailed fine-tuning of the chipset controlling the entire system.

4.2 BIOS Setup

The BIOS provides a Setup utility program for specifying the system configurations and settings. The BIOS ROM of the system stores the Setup utility. When you turn on the computer, the BIOS is immediately activated. Press the key immediately allows you to enter the Setup utility. If you are a little bit late pressing the key, POST (Power On Self Test) will continue with its test routines, thus preventing you from invoking the Setup.

If you still need to enter Setup, restart the system by pressing the "Reset" button or simultaneously pressing the <Ctrl>, <Alt> and <Delete> keys. You can also restart by turning the system Off and back On again.

The following message will appear on the screen:

```
Press <DEL> to Enter Setup
```


In general, press the arrow keys to highlight items, <Enter> to select, the <PgUp> and <PgDn> keys to change entries, <F1> for help, and <Esc> to quit.

When you enter the BIOS Setup utility, the *Main Menu* screen will appear on the screen. The Main Menu allows you to select from various setup functions and exit choices.

Warning: It is strongly recommended that you avoid making any changes to the chipset defaults.

These defaults have been carefully chosen by both AMI and your system manufacturer to provide the absolute maximum performance and reliability. Changing the defaults could make the system unstable and crash in some cases.

4.3 Main Settings



BIOS Setting	Description
System Date	Sets the date. Use the <Tab> key to switch between the Date elements.
System Time	Set the time. Use the <Tab> key to switch between the Time elements.

4.4 Advanced Settings

This section allows you to configure system features according to your preference.




4.4.1 Connectivity Configuration




BIOS Setting	Description
CNVI Mode	<p>This option configures Connectivity.</p> <p>Auto Detection – means that if Discrete solution is discovered it will be enabled by default. Otherwise Integrated solution (CNVi) will be enabled;</p> <p>Disable Integrated – disables Integrated Solution.</p>

4.4.2 CPU Configuration



BIOS Setting	Description
Intel (VMX) Virtualization Technology	When enabled, a VMM can utilize the additional hardware capabilities provided by Vanderpool Technology.
Active Performance Cores	Number of P-cores to enable in each processor package. Note: Number of cores and E-cores are looked at together. When both are (0,0), Pcode will enable all cores.
Active Efficient Cores	Number of E-cores to enable in each processor package. Note: Number of cores and E-cores are looked at together. When both are (0,0), Pcode will enable all cores.
Active SOC-North Efficient-cores	Number of SOC-North Efficient-cores to enable in SOC North
Hyper-Threading	Options; Enabled or Disabled

4.4.3 Power & Performance



BIOS Setting	Description
Intel Speedstep	Allows more than two frequency ranges to be supported
Intel Speed Shift Technology	Enable/Disable Intel Speed Shift Technology support. Enabling will expose the CPPC v2 interface to allow for hardware controlled P-states.
Turbo Mode	Enable/disable processor turbo mode.

4.4.4 System Agent (SA) Configuration

Aprio Setup - AMI

MainAdvancedSecurityBootSave & ExitMEBx

▶ Connectivity Configuration

▶ CPU Configuration

▶ Power & Performance

▶ System Agent (SA) Configuration

▶ PCH-IO Configuration

▶ PCH-FW Configuration

▶ Trusted Computing

▶ ACPI Settings

▶ LVDS (eDP/DP) Configuration

▶ F81804 Super IO Configuration

▶ F81804 Hardware Monitor

▶ USB Configuration

▶ Network Stack Configuration

▶ NVME Configuration

System Agent (SA) Parameters

++: Select Screen
t1: Select Item
Enter: Select
+/-: Change Opt.
F1: General Help
F2: Previous Values
F3: Optimized Defaults
F4: Save & Exit
ESC: Exit

Version 2.22.1293 Copyright (C) 2024 AMI

System Agent (SA) Configuration

▶ VMD setup menu


VMD Configuration settings

VMD Configuration


Enable VMD controller [Disable]

Enable/Disable to VMD controller

4.4.5 PCH-IO Configuration



4.4.6 PCH-FW Configuration



4.4.7 Trusted Computing

Aptio Setup - AMI		
Advanced		
TPM 2.0 Device Found	15.23	Enables or Disables BIOS support for security device. O.S. will not show Security Device. TCG EFI protocol and INT1A interface will not be available.
Firmware Version:	IFX	
Vendor:		
Security Device Support	[Enable]	
Active PCR banks	SHA256	
Available PCR banks	SHA256,SHA384	
SHA256 PCR Bank	[Enabled]	
SHA384 PCR Bank	[Disabled]	
Pending operation	[None]	
Platform Hierarchy	[Enabled]	
Storage Hierarchy	[Enabled]	
Endorsement Hierarchy	[Enabled]	
Physical Presence Spec Version	[1.3]	
TPM 2.0 InterfaceType	[TIS]	
Device Select	[Auto]	
		++: Select Screen F1: Select Item Enter: Select +/-: Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save & Exit ESC: Exit
Version 2.22.1293 Copyright (C) 2024 AMI		


BIOS Setting	Description
Security Device Support	Enables / Disables BIOS support for security device. OS will not show security device. TCG EFI protocol and INT1A interface will not be available.
SHA256/384 PCR Bank	Enables / Disables PCR Bank.
Pending operation	Schedule an operation for the security device. Note: Your computer will reboot during restart in order to change state of security device.
Platform Hierarchy	Enables / Disables platform hierarchy.
Storage Hierarchy	Enables / Disables storage hierarchy.
Endorsement Hierarchy	Enables / Disables endorsement hierarchy.
Physical Presence Spec Version	Select to tell O.S. to support PPI Spec Version 1.2 or 1.3. Note some HCK tests might not support 1.3.
Device Select	TPM 1.2 will restrict support to TPM 1.2 devices. TPM 2.0 will restrict support to TPM 2.0 devices. Auto will support both with the default set to TPM 2.0 devices if not found, TPM 1.2 devices will be enumerated.

4.4.8 ACPI Settings




BIOS Setting	Description
Enable ACPI Auto Configuration	Enables or disables system ability to hibernate (OS/S4 sleep state). This option may not be effective with some operating systems
Enable Hibernation	Enables / Disables the system ability to hibernate (OS/S4 Sleep State). This option may be not effective with some OS.

4.4.9 LVDS (eDP/DP) Configuration



BIOS Setting	Description
LVDS (eDP/DP) Support	<i>LVDS (eDP/DP) ON/OFF</i>
Panel Color Depth	Selects the panel color depth. Options: 18 bit, 24bit (VESA/JEIDA)
LVDS Channel Type	Chooses the LVDS as single or dual channel.
Panel Type	Panel Type (Resolution) Options: 800 x 480, 800 x 600, 1024 x 768, 1280 x 768, 1280 x 800, 1280 x 960, 1280 x 1024, 1366 x 768, 1440 x 900, 1600 x 900, 1600 x 1200, 1680 x 1050, 1920 x 1080, 1920 x 1200
LVDS Brightness Level Control	Options: Level-1 to Level-8

4.4.10 F81804 Super IO Configuration



BIOS Setting	Description
Serial Ports Configuration	<p>Sets parameters of serial ports.</p> <p>Enables / Disables the serial port and select an optimal setting for the Super IO device.</p>


Serial Port 1 Configuration



Serial Port 2 Configuration




4.4.11 F81804 Hardware Monitor




BIOS Setting	Description
CPU Smart Fan Control	Options include Disabled, 50°C, 60°C, 70°C and 80°C.
Temperatures / Voltages	These fields are the parameters of the hardware monitoring function feature of the motherboard. The values are read-only values as monitored by the system and show the PC health status.

4.4.12 USB Configuration



BIOS Setting	Description
XHCI Hand-off	This is a workaround for OSes without XHCI hand-off support. The XHCI ownership change should be claimed by XHCI driver.
USB Mass Storage Driver Support	Enables / Disables the support for USB mass storage driver.
USB Transfer time-out	The time-out value (1 / 5 10 / 20 secs) for Control, Bulk, and Interrupt transfers.
Device reset time-out	Gives seconds (10 / 20 / 30 / 40 secs) to delay execution of Start Unit command to USB mass storage device.
Device power-up delay	Max.time the device will take before it properly reports itself to the Host Controller. ' Auto ' uses default value: for a Root port it is 100ms, for a Hub port the delay is taken from Hub descriptor.

4.4.13 Network Stack Configuration




BIOS Setting	Description
Network Stack	Enable/Disable UEFI Network Stack
IPv4 PXE Support	If disabled, IPv4 PXE boot support will not be available.
IPv4 HTTP Support	If disabled, IPv4 HTTP boot support will not be available.
IPv6 PXE Support	If disabled, IPv6 PXE boot support will not be available.
IPv6 HTTP Support	If disabled, IPv6 HTTP boot support will not be available.
PXE boot wait time	Wait time in seconds to press ESC key to abort the PXE boot. Use either +/- or numeric keys to set the value
Media detect count	Number of times the presence of media will be checked. Use either +/- numeric keys to set the value.

4.4.14 NVMe Configuration




4.5 Security Settings



BIOS Setting	Description
Setup Administrator Password	Sets an administrator password for the setup utility.
User Password	Sets a user password.
Secure Boot	Secure Boot feature is Active if Secure Boot is enabled. Platform Key(PK) is enrolled and the system is in user mode. The mode change requires platform reset.
Secure Boot Mode	Secure Boot mode options: Standard or Custom. In Custom mode, Secure Boot Policy variables can be configured by a physically present user without full authentication.
Restore Factory Keys	Forces system to user mode. Install factory default Secure Boot key databases.
Reset to Setup Mode	Delete all Secure Boot key databases from NVRAM
Expert Key Management	Enables expert users to modify Secure Boot Policy variables without variable authentication.

4.6 Boot Settings



BIOS Setting	Description
Setup Prompt Timeout	Number of seconds to wait for setup activation key. 65535 (0xFFFF) means indefinite waiting.
Bootup NumLock State	Selects the keyboard NumLock state.
Quiet Boot	Enables / Disables Quiet Boot option.
FIXED BOOT ORDER Priorities	Sets the system boot order.

4.7 Save & Exit Settings



BIOS Setting	Description
Save Changes and Exit	Exits system setup after saving the changes.
Discard Changes and Exit	Exits system setup without saving any changes.
Save Changes and Reset	Resets the system after saving the changes.
Discard Changes and Reset	Resets system setup without saving any changes.
Save Changes	Saves changes done so far to any of the setup options.
Discard Changes	Discards changes done so far to any of the setup options.
Restore Defaults	Restores / Loads defaults values for all the setup options.
Save as User Defaults	Saves the changes done so far as User Defaults.
Restore User Defaults	Restores the user defaults to all the setup options.
Launch EFI Shell from filesystem device	Attempts to launch EFI shell application (Shell.efi) from one of the available filesystem devices.

4.8 MEBx



Appendix

This section provides the mapping addresses of peripheral devices and the sample code of watchdog timer configuration.

A. I/O Port Address Map

Each peripheral device in the system is assigned a set of I/O port addresses which also becomes the identity of the device.

Address	Device Description
0x0000EFA0-0x0000EFBF	SM Bus Controller
0x00000A00-0x00000A0F	Motherboard resources
0x00000A10-0x00000A1F	Motherboard resources
0x00000290-0x0000029F	Motherboard resources
0x0000002E-0x0000002F	Motherboard resources
0x0000004E-0x0000004F	Motherboard resources
0x00000061-0x00000061	Motherboard resources
0x00000063-0x00000063	Motherboard resources
0x00000065-0x00000065	Motherboard resources
0x00000067-0x00000067	Motherboard resources
0x00000070-0x00000070	Motherboard resources
0x00000080-0x00000080	Motherboard resources
0x00000092-0x00000092	Motherboard resources
0x000000B2-0x000000B3	Motherboard resources
0x00000680-0x0000069F	Motherboard resources
0x0000164E-0x0000164F	Motherboard resources
0x00000020-0x00000021	Programmable interrupt controller
0x00000024-0x00000025	Programmable interrupt controller
0x00000028-0x00000029	Programmable interrupt controller
0x0000002C-0x0000002D	Programmable interrupt controller
0x00000030-0x00000031	Programmable interrupt controller
0x00000034-0x00000035	Programmable interrupt controller
0x00000038-0x00000039	Programmable interrupt controller
0x0000003C-0x0000003D	Programmable interrupt controller
0x000000A0-0x000000A1	Programmable interrupt controller
0x000000A4-0x000000A5	Programmable interrupt controller
0x000000A8-0x000000A9	Programmable interrupt controller
0x000000AC-0x000000AD	Programmable interrupt controller
0x000000B0-0x000000B1	Programmable interrupt controller
0x000000B4-0x000000B5	Programmable interrupt controller
0x000000B8-0x000000B9	Programmable interrupt controller
0x000000BC-0x000000BD	Programmable interrupt controller
0x000004D0-0x000004D1	Programmable interrupt controller
0x00003050-0x00003057	Standard SATA AHCI Controller
0x00003040-0x00003043	Standard SATA AHCI Controller
0x00003020-0x0000303F	Standard SATA AHCI Controller

Address	Device Description
0x000003F8-0x000003FF	Communications Port (COM1)
0x000002F8-0x000002FF	Communications Port (COM2)
0x00000000-0x00000CF7	PCI Express Root Complex
0x00000D00-0x0000FFFF	PCI Express Root Complex
0x00000040-0x00000043	System timer
0x00000050-0x00000053	System timer
0x0000FFFF-0x0000FFFF	Intel(R) Active Management Technology - SOL (COM11)
0x00002000-0x000020FE	Motherboard resources
0x00001854-0x00001857	Motherboard resources

B. Interrupt Request Lines (IRQ)

Peripheral devices use interrupt request lines to notify CPU for the service required. The following table shows the IRQ used by the devices on board.

Level	Function
IRQ 4294967289~77	Intel(R) Ethernet Controller I226-LM #2
IRQ 4	Communications Port (COM1)
IRQ 3	Communications Port (COM2)
IRQ 4294967291	Intel(R) USB 3.20 eXtensible Host Controller - 1.20 (Microsoft)
IRQ 4294967293	PCI Express Root Port
IRQ 55-204	Microsoft ACPI-Compliant System
IRQ 256-511	Microsoft ACPI-Compliant System
IRQ 19	Intel(R) Active Management Technology - SOL (COM11)
IRQ 4294967290	Intel(R) USB 3.20 eXtensible Host Controller - 1.20 (Microsoft)
IRQ 4294967263	Intel(R) Management Engine Interface #1
IRQ 16	High Definition Audio Controller
IRQ 4294967294	PCI Express Root Port
IRQ 4294967276	Intel(R) Ethernet Controller I226-V #2

C. Watchdog Timer Configuration

The Watchdog Timer (WDT) is used to generate a variety of output signals after a user programmable count. The WDT is suitable for use in the prevention of system lock-up, such as when software becomes trapped in a deadlock. Under these sorts of circumstances, the timer will count to zero and the selected outputs will be driven.

Under normal circumstance, you will need to restart the WDT at regular intervals before the timer counts to zero.

Sample Code:

```
//-----
//
// THIS CODE AND INFORMATION IS PROVIDED "AS IS" WITHOUT WARRANTY OF ANY
// KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING BUT NOT LIMITED TO THE
// IMPLIED WARRANTIES OF MERCHANTABILITY AND/OR FITNESS FOR A PARTICULAR
// PURPOSE.
//
//-----
#include <dos.h>
#include <conio.h>
#include <stdio.h>
#include <stdlib.h>
#include "F81804.H"
//-----
int main (int argc, char*argv[]);
void EnableWDT(int);
void DisableWDT(void);
//-----
int main (int argc, char *argv[])
{
    unsigned char bBuf;
    unsigned char bTime;
    char **endptr;

    char SIO;

    printf("Fintek 81866 watch dog program\n");
    SIO = Init_ F81804();
    if (SIO == 0)
    {
        printf("Can not detect Fintek 81866, program abort.\n");
        return(1);
    }
    if (SIO == 0)

    if (argc != 2)
    {
        printf("Parameter incorrect!!\n");
        return (1);
    }
}
```

```

        bTime = strtol(argv[1], endptr, 10);
        printf("System will reset after %d seconds\n", bTime);

        if (bTime)
        {
            EnableWDT(bTime); }
        else
        {
            DisableWDT();}
        return 0;
    }
//-----
void EnableWDT(int interval)
{
    unsigned char bBuf;

    bBuf = Get_F81804_Reg(0x2B);
    bBuf &= (~0x20);
    Set_F81804_Reg(0x2B, bBuf);           //Enable WDTO

    Set_F81804_LD(0x07);                 //switch to logic device 7
    Set_F81804_Reg(0x30, 0x01);         //enable timer

    bBuf = Get_F81804_Reg(0xF5);
    bBuf &= (~0x0F);
    bBuf |= 0x52;
    Set_F81804_Reg(0xF5, bBuf);         //count mode is second

    Set_F81804_Reg(0xF6, interval);     //set timer

    bBuf = Get_F81804_Reg(0xFA);
    bBuf |= 0x01;
    Set_F81804_Reg(0xFA, bBuf);         //enable WDTO output

    bBuf = Get_F81804_Reg(0xF5);
    bBuf |= 0x20;
    Set_F81804_Reg(0xF5, bBuf);         //start counting
}
//-----
void DisableWDT(void)
{
    unsigned char bBuf;

    Set_F81804_LD(0x07);                 //switch to logic device 7

    bBuf = Get_F81804_Reg(0xFA);
    bBuf &= ~0x01;
    Set_F81804_Reg(0xFA, bBuf);         //disable WDTO output

    bBuf = Get_F81804_Reg(0xF5);
    bBuf &= ~0x20;
    bBuf |= 0x40;
    Set_F81804_Reg(0xF5, bBuf);         //disable WDT
}
//-----

```

```
//-----
//
// THIS CODE AND INFORMATION IS PROVIDED "AS IS" WITHOUT WARRANTY OF ANY
// KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING BUT NOT LIMITED TO THE
// IMPLIED WARRANTIES OF MERCHANTABILITY AND/OR FITNESS FOR A PARTICULAR
// PURPOSE.
//
//-----
#include " F81804.H"
#include <dos.h>
//-----
unsigned int F81804_BASE;
void Unlock_ F81804 (void);
void Lock_ F81804 (void);
//-----
unsigned int Init_ F81804(void)
{
    unsigned int result;
    unsigned char ucDid;

    F81804_BASE = 0x4E;
    result = F81804_BASE;

    ucDid = Get_ F81804_Reg(0x20);
    if (ucDid == 0x07)                //Fintek 81866
    {
        goto Init_Finish;
    }

    F81804_BASE = 0x2E;
    result = F81804_BASE;

    ucDid = Get_ F81804_Reg(0x20);
    if (ucDid == 0x07)                //Fintek 81866
    {
        goto Init_Finish;
    }

    F81804_BASE = 0x00;
    result = F81804_BASE;

Init_Finish:
    return (result);
}
//-----
void Unlock_ F81804 (void)
{
    outportb( F81804_INDEX_PORT, F81804_UNLOCK);
    outportb( F81804_INDEX_PORT, F81804_UNLOCK);
}
//-----
void Lock_ F81804 (void)
{
    outportb( F81804_INDEX_PORT, F81804_LOCK);
}
//-----
void Set_ F81804_LD( unsigned char LD)
{
    Unlock_ F81804();
    outportb( F81804_INDEX_PORT, F81804_REG_LD);
    outportb( F81804_DATA_PORT, LD);
}
```

```

        Lock_ F81804();
    }
    //-----
void Set_ F81804_Reg( unsigned char REG, unsigned char DATA)
{
    Unlock_ F81804();
    outputb( F81804_INDEX_PORT, REG);
    outputb( F81804_DATA_PORT, DATA);
    Lock_ F81804();
}
//-----
unsigned char Get_ F81804_Reg(unsigned char REG)
{
    unsigned char Result;
    Unlock_ F81804();
    outputb( F81804_INDEX_PORT, REG);
    Result = inportb( F81804_DATA_PORT);
    Lock_ F81804();
    return Result;
}
//-----

//-----
//
// THIS CODE AND INFORMATION IS PROVIDED "AS IS" WITHOUT WARRANTY OF ANY
// KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING BUT NOT LIMITED TO THE
// IMPLIED WARRANTIES OF MERCHANTABILITY AND/OR FITNESS FOR A PARTICULAR
// PURPOSE.
//
//-----
#ifndef F81804_H
#define F81804_H 1
//-----
#define F81804_INDEX_PORT ( F81804_BASE)
#define F81804_DATA_PORT ( F81804_BASE+1)
//-----
#define F81804_REG_LD 0x07
//-----
#define F81804_UNLOCK 0x87
#define F81804_LOCK 0xAA
//-----
unsigned int Init_ F81804(void);
void Set_ F81804_LD( unsigned char);
void Set_ F81804_Reg( unsigned char,
unsigned char); unsigned char
Get_ F81804_Reg( unsigned char);
//-----
#endif // F81804_H

```

D. Onboard Connector Reference Types

Function	Connector	Onboard Type	Compatible Mating Type
Audio	J2	Hao Guo Xing Ye DF11-12S-PA66H	Hirose DF11-12DS-2C
SATA HDD Power	J13	E-CALL 0110-071-040	JST XHP-4
Front Panel Setting	J16	E-CALL 2.5 mm-pitch pin header (Male)	Dupont 2.5mm-pitch (Female)
USB 2.0	J14	Hao Guo Xing Ye DF11-8S-PA66H	Hirose DF11-8DS-2C
COM2 Serial Port	J7, J17	Hao Guo Xing Ye DF11-10S-PA66H	Hirose DF11-10DS-2C
DC Power Input	J15	Hao Guo Xing Ye WAFER396-2S-WV	JST VHR-2N
Digital I/O	J6	Dupont 2.00 mm-pitch pin header (Male)	Dupont 2.00 mm-pitch (Female)
LCD Backlight	J2	E-CALL 0110-161-040	JST PHR-4.
LVDS	J4, J8	Hirose DF20G-20DP-1V	Hirose DF20A-20DS-1C

E. USB Power Control Bit

Function	Connector	Software Mapping
USB3 / USB2	CN5A / CN5B	Bit_0