GP1 4-Port Gigabit Ethernet PHY Line Card with PoE

- 4 Gigabit Ethernet on RJ45 connectors (M12 optional)
- Power over Ethernet (PoE+) PSE (all ports)
- LEDs for link and activity status
- -40 to +85°C with qualified components
- EN 50155 classTx (railways)
- PICMG CPCI-S.0 CompactPCI® Serial
- IEEE 1588v2 support (optional)



The GP1 is a 3U Gigabit Ethernet PHY line card, with optional PoE support, implemented as a CompactPCI® Serial board. It occupies one peripheral slot using a 4 HP front panel with four Gigabit Ethernet ports on RJ45 connectors. Alternatively, the GP1 can be supplied with four M12 connectors on the front panel (X-coded variants in preparation).

The GP1 is designed to work in combination with the G101 CompactPCI® Serial managed industrial Ethernet switch.

The GP1 features four connectors on the front panel, which can be used to create 4 ports of copper Gigabit


Ethernet. In addition, the card can act as Power over Ethernet (PoE) Power Sourcing Equipment (PSE), supplying other devices on all ports with power. Each interface supports a data transfer rate of 1 Gbit/s, and provides two LEDs to indicate the link and activity status.

The GP1 operates with a primary voltage supply of +12 V, which is provided via the rear CompactPCI® serial connector. All additional required voltages are generated onboard. It is fully compliant with the EN 50155 railway standard, qualified for a -40 to +85°C operation temperature and ready for coating.



02GP01- Data Sheet / 2015-06-18 Page

Diagram



02CP01- Data Sheet / 2015-06-18 Page 2

Technical Data

Key Features	 Four 10/100/1000BASE-T ports at front panel (Electrical isolation: 1500 Vrms) One common isolation group when PoE PSE is installed Optional PoE(+) Power sourcing support 		
Supported Protocols and Standards	 IEEE 1588v2 Optional IEEE 802.3 Standard Power over Ethernet support (IEEE 802.3 Section 2, Type 1 and 2 - classes 0, 1, 2, 3, 4) EEE (Energy Efficient Ethernet) 		
Power Over Ethernet Features	 Power over Ethernet functions on all ports PSE (Power Sourcing Equipment) function Supports supply classes 0 to 4 Supplies up to four powered devices (up to 60 W total) 		
Front Interfaces	 Ethernet Four RJ45 or M12 connectors, 1000BASE-TX (1 Gbit/s) Power over Ethernet PSE Status LEDs Two LEDs per channel Signal link status Signal link activity 		
Rear Interfaces	Serial GPIO (SGPIO)Quad Serial Gigabit Interface (QSGMII)		
Backplane Standard	■ CompactPCI® Specification PICMG CPCI-S.0 □ Peripheral slot with extensions (QSGMII)		
Supervision and Control	BITE Voltage SupervisionPoE Voltage monitoring		
Electrical Specifications	 Supply voltages +12 V (±3%) Power consumption 5 W without PoE support, 85 W max. with 60 W PoE 		
Mechanical Specifications	Dimensions: 3U, 4 HPWeight: 152 g		
Environmental Specifications	 Temperature range (operation): -40°C to +85°C Airflow 1.5m/s Temperature range (storage): -40°C to +85°C Relative humidity (operation): max. 95% non-condensing Relative humidity (storage): max. 95% non-condensing Altitude: -300 m to +2000 m Shock: 50 m/s², 30 ms Vibration (Function): 1 m/s², 5 Hz to 150 Hz (EN 61373) Vibration (Lifetime): 7.9 m/s², 5 Hz to 150 Hz (EN 61373) Conformal coating on request 		
Reliability	■ MTBF: 250.000 h @ 40°C according to IEC/TR 62380 (RDF2000)		
Safety	 Flammability UL 94V-0 Electrical Safety EN 50155 (Insulation) EN 50155 (Voltage) 		

02GP01- Data Sheet / 2015-06-18 Page 3

Technical Data

EMC	 EN 55022 (radio disturbance) EN 61000-4-2 (ESD Immunity) EN 61000-4-4 (burst)
-----	---

Ordering Information

Standard GP1 4-Port Gigabit Ethernet PHY Line Card with PoE Models	02GP01-00	SemiCus: 3U CompactPCI® Serial, 4 x RJ45 QSGMII port extender, no PoE, EEE and Sync-E support, -40 to +85°C
	02GP01-01	3U CompactPCI® Serial, 4 x RJ45 QSGMII port extender, PoE+ PSE, EEE and Sync-E support, -40 to +85°C
	02GP01-02	SemiCus: 3U CompactPCI $^{\circ}$ Serial, 4 x M12 QSGMII port extender, no PoE, EEE and Sync-E support, -40 to +85 $^{\circ}$ C, conformal coated
	02GP01-03	3U CompactPCI $^{\odot}$ Serial, 4 x M12 QSGMII port extender, PoE+ PSE, EEE and Sync-E support, -40 to +85 $^{\circ}$ C, conformal coated
Related Hardware	02G101-00	25-Port Gigabit Ethernet Managed Switch, $2x$ RJ45 + $1x$ SFP 2.5 Gbps on front, $10x$ GE + $3x$ QSGMII links on backplane, -40 to +85°C with qualified components
	02G101-01	24-Port Gigabit Ethernet Managed Switch, $3x\ M12$ on front, $9x\ GE+3x\ QSGMII$ links on backplane, -40 to +85°C with qualified components

Contact Information

Cermany

Germany	riance	OSA
MEN Mikro Elektronik GmbH	MEN Mikro Elektronik SAS	MEN Micro Inc.
Neuwieder Straße 3-7	18, rue René Cassin	860 Penllyn Blue Bell Pike
90411 Nuremberg	ZA de la Châtelaine	Blue Bell, PA 19422
Phone +49-911-99 33 5-0	74240 Gaillard	Phone (215) 542-9575
Fax +49-911-99 33 5-901	Phone +33 (0) 450-955-312	Fax (215) 542-9577
	Fax +33 (0) 450-955-211	
info@men.de	info@men-france.fr	sales@menmicro.com
www.men.de	www.men-france.fr	www.menmicro.com

France

The date of issue stated in this data sheet refers to the Technical Data only. Changes in ordering information given herein do not affect the date of issue. All brand or product names are trademarks or registered trademarks of their respective holders.

ΙΙςΔ

MEN is not responsible for the results of any actions taken on the basis of information in the publication, nor for any error in or omission from the publication.

MEN expressly disclaims all and any liability and responsibility to any person, whether a reader of the publication or not, in respect of anything, and of the consequences of anything, done or omitted to be done by any such person in reliance, whether wholly or partially, on the whole or any part of the contents of the publication.

The correct function of MEN products in mission-critical and life-critical applications is limited to the environmental specification given for each product in the technical user manual. The correct function of MEN products under extended environmental conditions is limited to the individual requirement specification and subsequent validation documents for each product for the applicable use case and has to be agreed upon in writing by MEN and the customer. Should the customer purchase or use MEN products for any unintended or unauthorized application, the customer shall indemnify and hold MEN and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim or personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that MEN was negligent regarding the design or manufacture of the part.

In no case is MEN liable for the correct function of the technical installation where MEN products are a part of.

Copyright © 2015 MEN Mikro Elektronik GmbH. All rights reserved.

02GP01- Data Sheet / 2015-06-18 Page 4